## **SIEMENS**

## Data sheet for SINAMICS Power module PM240-2

6SL3210-1PE21-8UL0 Article No.:

Client order no. : Order no. : Offer no.: Remarks :





Rated data		
Input		
Number of phases	3 AC	
Line voltage	380 480 V ±10 °	%
Line frequency	47 63 Hz	
Rated current (LO)	22.20 A	
Rated current (HO)	19.80 A	
Output		
Number of phases	3 AC	
Rated voltage	400V IEC	480V NEC 1)
Rated power (LO)	7.50 kW	10.00 hp
Rated power (HO)	5.50 kW	7.50 hp
Rated current (LO)	18.00 A	
Rated current (HO)	13.20 A	
Max. output current	27.00 A	
Pulse frequency	4 kHz	
Output frequency for vector control	0 200 Hz	
Output frequency for V/f control	0 550 Hz	
Overload capability		

Low Overload (LO)

1.1 x rated output current (i.e. 110 % overload) for 57 s with a cycle time of 300 s 1.5  $\times$  rated output current (i.e. 150 % overload) for 3 s with a cycle time of 300 s

High Overload (HO)

 $1.5\times$  output current rating (i.e., 150 % overload) for 57 s with a cycle time of 300 s 2  $\times$  output current rating (i.e., 200 % overload) for 3 s with a cycle time of 300 s

General tech. specifications		
Power factor $\lambda$	0.85	
Offset factor $\cos\phi$	0.95	
Efficiency η	0.97	
Sound pressure level (1m)	72 dB	
Power loss	0.20 kW	
Filter class (integrated)	-	


conditions		
Internal air cooling		
0.009 m <sup>3</sup> /s (0.325 ft <sup>3</sup> /s)		
1,000 m (3,280.84 ft)		
-5 40 °C (23 104 °F)		
-5 50 °C (23 122 °F)		
-25 55 °C (-13 131 °F)		
-25 55 °C (-13 131 °F)		
95 % RH, condensation not permitted		
Connections		
Plug-in screw terminals		
1.50 6.00 mm <sup>2</sup> (AWG 16 AWG 10)		
Plug-in screw terminals		
1.50 6.00 mm <sup>2</sup> (AWG 16 AWG 10)		
50 m (164.04 ft)		
100 m (328.08 ft)		
nical data		
IP20 / UL open type		
FSB		
3.00 kg (6.61 lb)		
100 mm (3.94 in)		
292 mm (11.50 in)		
165 mm (6.50 in)		
Standards		
dards		
dards UL, cUL, CE, C-Tick (RCM), SEMI F47		



## Data sheet for SINAMICS Power module PM240-2

Article No.: 6SL3210-1PE21-8UL0

Converter losses to IEC61800-9-2*		
Efficiency class	IE2	
Comparison with the reference converter (90% / 100%)	33.70 %	



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency (f). The values are valid for the basic version of the converter without options/components.

\*calculated values

<sup>&</sup>lt;sup>1)</sup>The output current and HP ratings are valid for the voltage range 440V-480V