SIEMENS

Data sheet for SINAMICS Power module PM230

6SL3223-0DE24-0BG1 Article No.:

Client order no. : Order no. : Offer no. : Remarks :





Rated data		
Input		
Number of phases	3 AC	
Line voltage	380 480 V ±10 %	
Line frequency	47 63 Hz	
Rated current (LO)	11.00 A	
Rated current (HO)	8.00 A	
Output		
Number of phases	3 AC	
Rated voltage	400V IEC	480V NEC 1)
Rated power (LO)	4.00 kW	5.00 hp
Rated power (HO)	3.00 kW	4.00 hp
Rated current (LO)	10.20 A	
Rated current (HO)	7.70 A	
Max. output current	15.40 A	
Pulse frequency	4 kHz	
Output frequency for vector control	0 200 Hz	
Output frequency for V/f control	0 550 Hz	
Overload capability		

Low Overload (LO)

1.1 x rated output current (i.e. 110 % overload) for 57 s with a cycle time of 300 s 1.5 \times rated output current (i.e. 150 % overload) for 3 s with a cycle time of 300 s

High Overload (HO)

 $1.5\times$ output current rating (i.e., 150 % overload) for 57 s with a cycle time of 300 s 2 \times output current rating (i.e., 200 % overload) for 3 s with a cycle time of 300 s

General tech. specifications		
Power factor λ	0.90	
Offset factor $\cos\phi$	0.95	
Efficiency η	0.97	
Sound pressure level (1m)	63 dB	
Power loss	0.14 kW	
Filter class (integrated)	Class B	


tted		
Connections		
Mechanical data		



Data sheet for SINAMICS Power module PM230

Article No.: 6SL3223-0DE24-0BG1

Converter losses to IEC61800-9-2*		
Efficiency class	IE2	
Comparison with the reference converter (90% / 100%)	31.30 %	



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency (f). The values are valid for the basic version of the converter without options/components.

*calculated values

¹⁾The output current and HP ratings are valid for the voltage range 440V-480V