

MLFB-Ordering data

6SE6440-2UE31-5DA1



Figure similar

Client order no. : Item no. :
Order no. : Consignment no. :
Offer no. : Project :
Remarks :

| Rated data | | General | General tech. specifications | | |
|----------------------------------|---------------------|---------------------|------------------------------|--|--|
| Input | | Power factor λ | 0.95 | | |
| Number of phases | 3 AC | Efficiency η | 0.96 | | |
| Line voltage | 500 600 V ±10 % | Amb | Ambient conditions | | |
| Line frequency | 47 63 Hz | Cooling | Fan | | |
| Rated current (LO) | 30.00 A | Ambient temperature | | | |
| Rated current (HO) | 24.90 A | Operation (LO) | -10 40 °C | | |
| Output | | Operation (HO) | -10 50 °C | | |
| Number of phases | 3 AC | Transport | -40 70 °C | | |
| Rated voltage | 600 V | Storage | -40 70 °C | | |
| Rated power (LO) | 18.50 kW / 25.00 hp | | | | |
| Rated power (HO) | 15.00 kW / 20.00 hp | | | | |
| Rated current (LO) | 27.00 A | | | | |
| Rated current (HO) | 22.00 A | | | | |
| Pulse frequency | 4000 Hz | | | | |
| Output frequency for V/f control | 0 650 Hz | | | | |

As a result of legal stipulations, a limit to 550 Hz is in production

Overload capability

Low Overload (LO)

140 % output current for 3 s, followed by 110 % output current for 57 s followed by 100 % output current for 240 s in a 300 s cycle time

High Overload (HO)

150 % output current for 60 s, followed by 100 % output current for 240 s in a 300 s cycle time

Page 1 of 2



MLFB-Ordering data

6SE6440-2UE31-5DA1



Figure similar

| Mechanical data | | Co | Connections | | |
|-------------------------|---------------------|-------------------------|-------------|--|--|
| Degree of protection | IP20 / UL open type | Motor end | | | |
| Frame size | FSD | Conductor cross-section | 35.00 mm² | | |
| Net weight | 16.00 kg | | | | |
| Width | 275.0 mm | | | | |
| Height | 520.0 mm | | | | |
| Depth | 245.0 mm | | | | |
| Inputs / outputs | | | | | |
| Standard digital inputs | | | | | |
| Number | 6 | | | | |
| Relay output | | | | | |
| Number | 3 | | | | |
| Analog inputs | | | | | |
| Number | 2 | | | | |
| Analog outputs | | | | | |
| Number | 2 | | | | |
| PTC/ KTY interface | | | | | |
| Number | 1 | | | | |
| | | | | | |