

MLFB-Ordering data

6SL3120-1TE32-0AA4



Client order no. : Order no. : Offer no. : Remarks : Item no. :
Consignment no. :
Project :

Rated data		Ambient conditions		
DC link voltage	DC 510 720 V			
Electronics power supply	DC 24 V -15 % / +20 %	Installation altitude (withous derating)	out	
Current demand, max.	1.50 A	Cooling ⁸⁾		
DC-link current I _d	200.0 A	Cooling air requirement		
Output current		Ambient temperature		
Rated value I _N	200.0 A	During operation		
Base load current I _H	141.0 A	Connections		
For S6 duty (40%) I _{S6}	230.0 A	Motor end		
I _{max}	282.0 A	Version		
Type rating ²⁾		Conductor cross-section		
Based on _{IN}	107.0 kW	PE connection		
Based on _{IH}	76.0 kW			
Rated pulse frequency	4.00 kHz	Max. motor cable length		
Current carrying capacity		Shielded		
DC link busbars	200 A	Unshielded		
24 V busbars	20 A			
DC link capacitance	3995 μF		Standards	
Output frequency for servo control 5)	0 650 Hz	Compliance with standards		
Output frequency for V/f control ⁶⁾	0 600 Hz	Safety Integrated		

0 ... 300 Hz

Output frequency for vector control 7)



MLFB-Ordering data

6SL3120-1TE32-0AA4



Mechanical data		General te	General tech. specifications		
Line side		Sound pressure level (1m)	73.0 dB		
Width	300.00 mm (11.81 in)	Power loss, typ./max. 9)	2.03 kW / 2.09 kW		
Height	629.00 mm (24.76 in)				
Depth	270.00 mm (10.63 in)				
Degree of protection	IP20 / UL open type				
Type of construction	Booksize				
Net weight	21.0 kg (46.30 lb)				

- 7) Observe the dependency between max. output frequency and current derating.
- 8) Power units with intensified air cooling thanks to integrated fan
- 9) Power loss of the Motor Module with rated power including losses of the 24 V DC electronics power supply

²⁾ Rated output of a typical standard asynchronous motor at 400 V 3 AC $\,$

⁵⁾ With rated output current (max. output frequency 1300 Hz at a current controller cycle of 62.5 µs, pulse frequency 8 kHz, 60 % permissible output current). Observe the dependency between max. output frequency and current derating. At present, the output frequency is limited to 550 Hz, the values stated apply with the high output frequency license.

⁶⁾ Observe the dependency between max. output frequency and current derating. At present, the output frequency is limited to 550 Hz, the values stated apply with the high output frequency license.