Data sheet for three-phase Squirrel-Cage-Motors SIMOTICS



2024-04-19

1/1

Motor type : 1CV1220B SIMOTICS SD - 225 S - IM B5 - 4p Offer no. Client order no. Item-No Order no. Consignment no. Project Remarks Safe Area **Electrical data** -/η 3) Δ/Υ U f Р Р ī М cosφ ³⁾ I_A/I_N M_A/M_N M_K/M_N IE-CL n [V] [Hz] [kW] [hp] [A] [1/min] [Nm] 4/4 3/4 4/4 T_I/T_N T_B/T_N 2/4 3/4 2/4 I_I/I_N **DOL duty (S1)** - 155(F) to 130(B) 400 Δ 50 37.00 69.00 1475 240.0 91.2 91.6 91.1 0.85 0.81 0.71 7.0 2.3 3.2 IE1 690 37.00 -/-40.00 0.81 50 1475 240.0 91.2 91.6 91.1 0.85 0.71 7.0 2.3 3.2 IE1 Δ 2.3 60 42.50 -/-93.0 93.3 92.5 0.74 7.0 IE1 460 67.00 1775 230.0 0.86 0.83 3.2 IM B5 / IM 3001 FS 225 S IEC/EN 60034 IEC, DIN, ISO, VDE, EN IP55 Environmental conditions: -20 °C - +40 °C / 1000 m Locked rotor time (hot / cold): 13.2 s | 22.9 s Mechanical data Sound level (SPL / SWL) at 50Hz|60Hz 68 / 82 dB(A) 2) 3) 72 / 86 dB(A) 2) 3) Vibration severity grade Α Moment of inertia 0.3700 kg m² Thermal class F S1 Bearing DE | NDE 6213 Z C3 6213 Z C3 Duty type bearing lifetime Direction of rotation bidirectional $L_{10mh}\,F_{Rad\,\,min}$ for coupling operation $50|60Hz^{\,1)}$ 40000 h 32000 h Frame material cast iron Regreasing device Without Net weight of the motor (IM B3) 260 kg Coating (paint finish) Standard paint finish C2 Grease nipple Locating bearing NDE RAL7030 Type of bearing Color, paint shade Condensate drainage holes With (standard) Motor protection (A) without (Standard) External earthing terminal With (standard) Method of cooling IC411 - self ventilated, surface cooled Terminal box Terminal box position top Max. cross-sectional area $35 \ mm^2$ Material of terminal box cast iron Cable diameter from ... to ... 27 mm - 35 mm Type of terminal box TB1 L01 2xM50x1,5 Cable entry Contact screw thread М8 Cable gland 2 plugs 1) L_{10mh} according to DIN ISO 281 10/2010 3) Value is valid only for DOL operation with motor design IC411 IA/IN = locked rotor current / current nominal 2) at rated power / at full load M_A/M_N = locked rotor torque / torque nominal M_K/M_N = break down torque / nominal torque Transmittal, reproduction, dissemination and/or editing of this document as well as utilization of its contents and communication thereof to others without express authorization are prohibited. Offenders will be held liable for payment of damages. All rights created by patent grant or registration of a utility model or design patent are reserved Responsible department Technical reference Created by Approved by Technical data are subject to change! There may be Link documents discrepancies between calculated and rating plate IN LVM SPC Created automatically Document type Document status Released Technical data sheet **SIEMENS** Document number 1LE1502-2BB03-4FA4 TDS-240419-215428 Revision Creation date Language Page Restricted

© Innomotics 2024